

DECODE
SECTION B - Z SIGNALS

SIGNAL	QUESTION	ANSWER, ADVICE OR ORDER
ZAA		You are not observing proper circuit discipline.
ZAB		Your speed key is improperly adjusted.
ZAC		Cease using speed key.
ZAD		Your operating signal (made at...) received as...(1. Not understood; 2. Not held).
ZAE		I am unable to receive you. Receipt through...
ZAF	Will you patch me through to...(via you or...)?	I am about to patch you through to... (via...).
ZAG		Break...(1. Go ahead with next tape; 2. Go back...feet; 3. Advance your key tape to reference mark number and repeat last transmission (or transmission...)).
ZAH		Unable to relay message...in present form (1. Not in prescribed format; 2. Format lines...incorrect; 3. No on-line facility available; 4. Call signs not encrypted; 5. Text not encrypted). We file. Transmit correctly prepared message to all addressees (or to...).
ZAI		Run... (1. Caller; 2. Test tape; 3. Synchronizing tape; 4. Traffic tape; 5. Marking signals; 6. Spacing signals; 7. Reversals; 8. Run teletypewriter space bar signals). 9. Datel test at....bd
ZAJ		I have (or...has) been unable to break you.

DECODE

SIGNAL	QUESTION	ANSWER, ADVICE OR ORDER
ZAK		Transmission on...klz (or MHz) suspended until...(or was suspended at...) on account of electrical hazards (or...)
ZAL		I am closing down (until...) due to...
ZAM		I am unable to obtain reply from teleprinter switchboard...(for connection to...). Request you call him (or other intermediate switchboard) for me.
ZAN		Transmit only messages of and above precedence...
ZAO		I cannot understand your speech. Use radiotelegraph.
ZAP	Shall I work...(1. Simplex; 2. Duplex; 3. Diplex; 4. Multiplex; 5. Single Sideband; 6. With automatic error correction system; 7. Without automatic error correction system)?	Work...(1. Simplex; 2. Duplex; 3. Diplex; 4. Multiplex; 5. Single Sideband; 6. With automatic error correction system; 7. Without automatic error correction system).
ZAQ		The last word (or group)... (1. Received from you was...; 2. Transmitted to you was...).
ZAR		This is my...request (or reply). (1. First; 2. Second; 3. Third; etc.).
ZAS		Rerun all tapes run on...since... (1. Your present frequency; 2. ...kHz (or MHz); 3. Call sign...; 4. This channel or...channel).
ZAT		Am preparing traffic (perforating tape) for transmission.
ZAU	What is teletype range taken on my signal(s)?	Teletype range taken on your signal(s) is...to...

DECODE

SIGNAL	QUESTION	ANSWER, ADVICE OR ORDER
ZBR	Shall I send by... (1. Direct (R) method; 2. Broadcast (F) method; 3. Intercept (I) method; 4. Repeat back (G) method)?	Send by...(1. Direct (R) method; 2. Broadcast (F) method; 3. Intercept (I) method; 4. Repeat back (G) method).
ZBS		Your...(1. Dots are too heavy; 2. Dots are too light; 3. Dots are varying in bias; 4. Dot spacing is bad; 5. Dots are missing; 6. Dots are burring).
ZBT	How do you count following text group(s) ...?	Text group(s)...should be counted as...group(s).
ZBU		Report when you are in radio communication with...
ZBV		Answer me (or...) on...kHz (or MHz).
ZBW	Will you shift (or ask ...to shift) to trans- mit on...kHz (or MHz)?	I am (or...is) shifting to transmit on...kHz (or MHz).
ZBX	Will you shift (or ask... to shift) to receive on...kHz (or MHz)?	I am (or...is) shifting to receive on...kHz (or MHz).
ZBY		Pass...(1. On broadcast...; 2. On Broadcast...single operator; 3. On Broadcast...two operator period; 4. On Broadcast...general periods only).
ZBZ	What is the printing accuracy of my signals (or those of...)?	The printing accuracy of your signals (or those of...) is...(1. Totally corrupt; 2. Very corrupt; 3. Partly corrupt rendering traffic unaccept- able; 4. Occasionally corrupt but traffic acceptable. 5. Perfect - no corruption).