

DECODE

SIGNAL	QUESTION	ANSWER, ADVICE OR ORDER
ZEA		Pass plain language copy to... by secure means.
ZEB		This is a reprocessed ICAO message.
ZEC	Have you received message...?	Message...(1. Not received; 2. Unidentified. Give better identifying data).
ZED		The following confirmatory information as received is at variance with the text.
ZEE		Request message...be transmitted.
ZEF		This message has been read (received or intercepted) from a ship at sea.
----- ZEG		This message is not to be decrypted or reported outside the communication center in...(1. Aggressor force; 2. Friendly force).
ZEH		Accuracy of...portion of following message (or message...) is doubtful. Correction or confirmation will be forwarded when received. (1. Heading; 2. Text; 3. Group...to...)
ZEI		Accuracy is doubtful of heading of message received as follows... Check to station of origin if necessary and repeat.
ZEJ		Replies to this message (or message...) are to be sent now (or at...)
ZEK		No answer is required.

## DECODE

SIGNAL	QUESTION	ANSWER, ADVICE OR ORDER
ZEL	Is message...a correction to message...which was previously transmitted with doubtful or missing groups (words)?	This message is a correction (to message...) (transmitted by...). Note: May only be used in conjunction with ZDG.
ZEM		
ZEN		This message has been delivered by a separate transmission or by other means (1. Messenger/courier; 2. Mail) to the addressee(s) immediately following this operating signal.
ZEO		Transmit this message by rapid means when no charges are involved and to all others by mail.
ZEP		This message (or message...) was incompletely received. Each word or group missed, which is indicated by position of ZEP in the message, will be forwarded as soon as obtained.
ZEQ		Message...has been (1. Missent to this station. Received at...z. Message protected; 2. Missent to this station and unable to protect delivery due to.... Request you re-transmit to the appropriate called station(s); 3. Misrouted to this station and has been rerouted to ...at....z. Recommend corrective action; 4. Misrouted to this station and unable to protect delivery (for...) due to... Request your station protect delivery; 5. Routed to this station in format line 2, but without delivery responsibility in format lines 7 or 8. Advise.)
ZER		This is a multiple-address or book message tape containing...routing indicators in the routing line for which the station called in the pilot is responsible.
ZES		Your message...has been received...(1. Incomplete; 2. Garbled). Request retransmission.
ZET		Message...has been protected and no further action by...is required.
ZEU		Exercise (drill) message.

DECODE

SIGNAL	QUESTION	ANSWER, ADVICE OR ORDER
ZEV	Request you acknowledge message...	Message (or message...) is acknowledged.
ZEW		Your attention is invited, for... (1. Action; 2. Information), to message... which is in your files.
ZEX		This is a book message and may be delivered as a single-address message to addressees for whom you are responsible.
ZEY		This message (or message...) has been (or will be) put on the... broadcast schedules (serial number...)
ZEZ		When delivery is effected of this book message to addressee by commercial means, or when copy is forwarded to confirm message previously delivered by telephone it is to be sent as a single address message. (May only be used in conjunction with ZEX.)
ZFA		Following message has been read (received or intercepted).
ZFB		Pass this message to... (1. on arrival; 2. On return to base).
ZFC	Have you received (or sent) the executive signal ("Execute") for message...?	Executive signal ("Execute") for last message (or following message) has been made (or was made at...).
ZFD		This message is a suspected duplicate.
ZFE		Pass message...(which is in your files) to addressee(s) for whom you are responsible using the indicated supplementary heading.

DECODE

SIGNAL	QUESTION	ANSWER, ADVICE OR ORDER
ZFF		Inform me when this message (or message...) has been received by... (addressee designation) or by... (1. Action addressee(s); 2. Information addressee(s); 3. All addressees; 4. Action addressee's/addressees' message center; 5. Information addressee's/addressees' message center; 6. All addressees' message center). (NOTE: AUTHORIZED FOR USE ON GENERAL MESSAGES).
ZFG		This message is an exact duplicate of a message previously transmitted.
ZFH		This message (or message...) is being (or has been) passed to you (or...) for... (1. Action; 2. Information; 3. Comment) (at the request of...)
ZFI	Is there any reply to message...?	There is no reply to message...
ZFJ		Message(s)...number(s)...not transmitted on this schedule (or on schedule...) are no longer needed.
ZFK	Does message...(or station serial number...) concern me (or...)?	Message...(or station serial number...) ..(1. Does not concern you (or...); 2. No longer concerns you (or...)).
ZFL	Was there any traffic addressed to me on... broadcast schedule between serial numbers... and ....?	Following traffic was addressed to you on...broadcast schedule between serial numbers... and ...
ZFM		Message(s) serial number(s)...(to ...) which was (were) transmitted during unserviceability of one or more transmitters, simultaneously keyed, will now be repeated.
ZFN		

DECODE

SIGNAL	QUESTION	ANSWER, ADVICE OR ORDER
ZFO		Message...is being delivered as a basegram message.
ZFP		Basegram.
ZFQ		Two messages (...and...) received under channel number (or station serial number) ... Both released.
ZFR		Cancel transmission...(made under channel or station serial number ...).
ZFS		Make message...same channel or station serial number as this procedure message.
ZFT		Message...received without channel number (or station serial number) following message bearing channel number (or station serial number) ...Message released.
ZFU		Channel numbers...and...preceded message... Lower number recorded and higher number blanked.
ZFV		Message...containing channel number...separated by portions of the message, released subject to correction. Take necessary action to provide corrected copy.
ZFW		BLANK channel number(s)...Forward message...as channel number...
ZFX		Channel number (or station serial number)...is open.
ZFY		
ZFZ		